

Version: 20170119

Company	Name	Tech.	Power / W	Socket	EAN	Eaton Profile ID	max nr. of LED's by Peak or RMS Current - 250W DA	Maximum nominal LED Power / W - 250W DA	Dimming profile						Best Standard Profile (1st-OK, 2nd Average OK)	Comment
									Dim Type	MIN	MID	MAX	Time / Periods	WUT/STU P		
Eglo	LED G9 2,5W	LED ND	2,5	G9	9002759114619	0,6	n.a.	n.a.	Switch	100	100	100	0	ON/OFF only		
ESTO Lighting	LED Lamp A60	LED ND	5,0	E27	9003348106428	0,6	n.a.	n.a.	Switch	100	100	100	0	ON/OFF only		
ESTO Lighting	LED Filament Candle 2W	LED ND	2,0	E14	9003348117264	0,6	n.a.	n.a.	Switch	100	100	100	0	ON/OFF only		
ESTO Lighting	LED G9 1,5W 3000K	LED ND	1,5	G9	9003348102895	0,6	n.a.	n.a.	Switch	100	100	100	0	ON/OFF only		
ESTO Lighting	LED Spot 3W GU10	LED ND	3,0	GU10	9003348872590	0,6	n.a.	n.a.	Switch	100	100	100	0	ON/OFF only		
Globo	LED Kerze E14 3W	LED ND	3,0	E14	9007371224708	0,6	n.a.	n.a.	Switch	100	100	100	0	ON/OFF only		
Globo	LED G9 1,9W 3000K	LED ND	1,9	G9	9007371250806	0,6	n.a.	n.a.	Switch	100	100	100	0	ON/OFF only		
Homeware	LED-Leuchtmittel Kerze 4W E14	LED ND	4,0	E14	9008420107881	0,6	n.a.	n.a.	Switch	100	100	100	0	ON/OFF only		
Ikea / LEDARE	LED-Lampe	LED ND	8,0	GU10	80255907222379	0,6	n.a.	16	Switch	100	100	100	0	ON/OFF only		
Jedi Lighting	JEDI Lighting 230 V E27 7.5 W	LED FB	7,5	E27	JE01249	0,6	n.a.	n.a.	Switch	100	100	100	0	ON/OFF only		
Livarno	LED-Lampe mit Bewegungssensor	LED ND BM	6,0	E27		0,6	n.a.	n.a.	Switch	100	100	100	0	ON/OFF only		
Megaman	Megaman 230 V GU9 2 W	LED ND	2,0	GU9	4020856491223	0,6	n.a.	n.a.	Switch	100	100	100	0	ON/OFF only		
Megaman	Megaman 230 V E14 3 W	LED ND	3,0	E14	4020856210503	0,6	n.a.	n.a.	Switch	100	100	100	0	ON/OFF only		
Müller Licht	LED Leuchtmittel E27 EB1400362	LED ND	3,0	E27	20016630	0,6	n.a.	n.a.	Switch	100	100	100	0	ON/OFF only		
Müller Licht	LED Blub 3W E14	LED ND	3,0	E14	4018412029973	0,6	n.a.	n.a.	Switch	100	100	100	0	ON/OFF only		
MX-Logistika SL	LED Candle 3W E14	LED ND	3,0	E14	9009852000115	0,6	n.a.	n.a.	Switch	100	100	100	0	ON/OFF only		
Nice Price	LED 230V (nicht dimmbar)	LED ND	4,0	GU10	4000870033937	0,6	n.a.	5	Switch	100	100	100	0	ON/OFF only		
OK	Energiesparlampe (nicht dimmbar)	ESL ND	20,0	E27	ET-2-20W-E27	0,6	n.a.	6	Switch	100	100	100	0	ON/OFF only		
RS	Kerzenlampe 60 LED ES/E27 3W Warmweiß	LED ND	3,0	E27	7158272	0,6	n.a.	14	Switch	100	100	100	0	ON/OFF only		
SoftLED	Value Glühfaden-Kerze 230 V E14 2 W	LED ND	2,0	E14	9120050690837	0,6	n.a.	n.a.	Switch	100	100	100	0	ON/OFF only		
Sygonix	125 mm sygonix 230 V E27 3 W	LED ND	3,0	E27	4051462039141	0,6	n.a.	8	Switch	100	100	100	0	ON/OFF only		
Verbatim	Candle 1900K E14 2.5W 50lm Non Dim	LED ND	2,5	E14	023942522430	0,6	n.a.	n.a.	Switch	100	100	100	0	ON/OFF only		
Verbatim	LED-Reflektorlampe 220 → 240 V GU10, 4 W	LED ND	4,0	GU10	52607	0,6	n.a.	4	Switch	100	100	100	0	ON/OFF only		
Vosla Lighting	LED-Candle clear	LED ND	3,0	E14	4250686551525	0,6	n.a.	n.a.	Switch	100	100	100	0	ON/OFF only		
Vosla Lighting	LED-Candle clear	LED ND	2,0	E14	4250686550733	0,6	n.a.	n.a.	Switch	100	100	100	0	ON/OFF only		
Ikea / LEDARE	LED-Lampe	LED	13,0	E27	002.574.82	31.1	n.a.	5	65 Auto - TE	13	30	75	0	0 LED 4, R/L/C Standard		
Ikea / LEDARE	LED-Lampe	LED	16,5	E27	202.492.26	31.2	n.a.	7	82,5 Auto - TE	10	30	70	0	0 LED 4, R/L/C Standard	Good dimming experience	
Ikea / LEDARE	LED-Lampe	LED	10,0	E27	602.553.62	31.3	n.a.	5	70 Auto - TE	12	34	75	0	0 LED 4, R/L/C Standard		
Megaman	LED Lampe	LED	11,0	E27	4020856000159	32.1	n.a.	16	176 Auto - TE	18	30	55	0	0 LED 3		
Megaman	LED Filament lamp - EL.Nr.: MM05245	LED	5,5	E27	4892657052459	32.10	n.a.	31	170,5 Auto - TE	35	44	60	0	0 LED 1	very narrow dimming range	
Megaman	LED Filament lamp - EL.Nr.: MM05381	LED	3	E27	4892657053814	32.11	n.a.	41	123 Auto - TE	35	44	60	0	0 LED 1	very narrow dimming range	
Megaman	LED Filament lamp - EL.Nr.: MM05243	LED	3,2	E14	4892657052435	32.12	n.a.	41	131,2 Auto - TE	35	44	60	0	0 LED 1		
Megaman	LED PAR16 Dim to Warm - EL.Nr.: MM05238	LED	6	GU10	4892657052381	32.13	n.a.	31	186 Auto - TE	15	37	70	0	0 LED 4, LED 2		
Megaman	LED PAR16 - EL.Nr.: MM06364	LED	5,5	GU10	4892657063646	32.14	n.a.	31	170,5 Auto - TE	15	48	80	0	0 R/L/C Standard (1%)	Good dimming experience	
Megaman	LED G9 - EL.Nr.: MM03829	LED	3	GU9	4892657038293	32.15	n.a.	62	186 Auto - TE	35	50	70	0	0 R/L/C Standard	flickers easily	
Megaman	ESL CL809d	ESL	9,0	E14	MM46602	32.2	n.a.	8	72 Auto - TE	30	45	65	0	3 ESL/CFL		
Megaman	LED Lampe	LED	4,0	E14	4020856210282	32.3	n.a.	40	160 Auto - TE	20	28	40	0	0 LED 5, LED 1		
Megaman	ESL GSU111d	ESL	11,0	E27	MM46012	32.4	n.a.	10	110 Auto - TE	30	45	65	0	3 ESL/CFL		
Megaman	LED Classic -EL.Nr.: MM06412	LED	7	E27	4892657064124	32.5	n.a.	25	175 Auto - TE	12	30	70	5	1 R/L/C Standard (1%)		
Megaman	LED Classic Dim to Warm - EL.Nr.: MM05236	LED	7	E27	4892657052367	32.6	n.a.	27	189 Auto - TE	15	34	50	0	0 LED 3	Good dimming experience	
Megaman	LED Classic Dim to Warm - EL.Nr.: MM05235	LED	6	E27	4892657052350	32.7	n.a.	27	162 Auto - TE	20	32	50	0	0 LED 5, LED 2	flickers easily	
Megaman	LED Globe - EL.Nr.: MM07196	LED	13	E27	4892657071962	32.8	n.a.	15	195 Auto - TE	20	36	70	0	0 LED 2		
Megaman	LED Classic Dim to Warm - EL.Nr.: MM05237	LED	10,5	E27	4892657052374	32.9	n.a.	22	231 Auto - TE	12	36	70	0	0 R/L/C Standard (1%)	Good dimming experience	
Verbatim	LED E27 GLS lamp IP65	LED	7,5	E27	023942522201	33.1	n.a.	15	112,5 Auto - TE	12	30	60	0	0 LED 3	Good dimming experience	
Verbatim	GLS E27 8W 2700K 530lm Dimmable	LED	8,0	E27	023942521488	33.2	n.a.	12	96 Auto - TE	20	45	70	0	0 LED 2		
Verbatim	LED-Reflektorlampe 220 bis 240 V, 7.3 W	LED	7,3	GU10	023942522348	33.3	n.a.	15	109,5 Auto - TE	18	36	70	0	0 LED 4, LED 1		
LG	LED-Lampe	LED	12,8	E27	8808992455912	34.1	n.a.	5	64 Auto - TE	20	45	75	0	0 LED 2		
Ledon	LED-Lampe A65	LED	10,0	E27	9009453001511	35.1	n.a.	16	160 Auto - TE	12	28	60	0	0 LED 3	quick flash when starting but then good	
Sygonix	78 mm sygonix 230 V E27 4.5 W	LED	4,5	E27	4051462041670	35.1	n.a.	8	36 LE	16	37	65	0	0 LED 7		
Ledon	LED-Lampe A60	LED	10,0	E27	9009453003560	35.2	n.a.	5	50 Auto - TE	25	45	75	0	0 LED 1	Good dimming experience	
Sygonix	85 mm sygonix 230 V E14 5 W	LED	5,0	E14	4051462041434	35.2	n.a.	8	40 Auto - TE	20	40	65	0	0 LED 1		
Ledon	LED-Tropfen P45	LED	5,0	E14	9120044927925	35.3	n.a.	14	70 Auto - TE	25	40	70	0	0 LED 1		
Ledon	LED-Spot MR16	LED	5,0	GU10	9009453002372	35.4	n.a.	8	40 Auto - TE	20	40	75	0	0 LED 2		
GE	LED bulb dimmable lamp 4W P45 E27 240V	LED	4,0	E27	0043168973106	36.1	n.a.	8	32 Auto - TE	25	45	65	0	0 LED 1		
GE	Dimmable LED 8w GLS E27 lamp 2700K 470lm	LED	8,0	E27	0043168987837	36.2	n.a.	17	136 Auto - TE	8	25	65	0	0 LED 4, LED 3		
GE	LED Spot Energy Smart	LED	5,0	GU10	43168984492	36.3	n.a.	20	100 Auto - TE	24	45	70	0	0 LED 1		
Renkforce	Renkforce 230 V E27 5.5 W	LED	5,5	E27	4016138833683	38.1	n.a.	7	38,5 Auto - TE	25	45	75	0	0 LED 1		
Vosla Lighting	LED-Bulb clear	LED	3,5	E27	4250686550689	39.1	n.a.	12	42 Auto - TE	28	34	45	0	0 LED 6, LED 1	flickers easily	
Vosla Lighting	LED-Bulb clear	LED	5,5	E27	4250686550702	39.2	n.a.	12	66 Auto - TE	30	40	55	0	0 LED 6, LED 1	flickers easily	
SoftLED	Value Glühfaden-Birne 230 V E27 4 W	LED	4,0	E27	9120050690820	40.1	n.a.	2	80 Auto - TE	20	33	50	0	0 LED 5, LED 2	Very limited dimming range, flickers easily	
Philips	MASTER LED Spot	LED	8,0	GU10	871829168233200	41.1	n.a.	4	32 Auto - TE	26	44	70	0	0 LED 1		
Philips	MASTER LED Candle	LED	3,5	E14	871829174321700	41.10	n.a.	26	91 Auto - TE	12	30	45	0	0 LED 3	Good dimming experience	
Philips	CorePro LED Luster	LED	6,0	E14	871829176240900	41.11	n.a.	20	120 Auto - TE	20	36	75	0	0 LED 2		
Philips	LED Candle	LED	4,0	E14	871829167078900	41.12	n.a.	40	160 Auto - TE	16	34	55	0	0 LED 3	Good dimming experience	
Philips	Tornado ESL	ESL	20,0	E27	871016339470110	41.13	n.a.	6	120 Auto - TE	25	38	65	0	0 LED 1		
Philips	LED Spot	LED	4,2	GU10	871829119286200	41.14	n.a.	40	168 Auto - TE	12	24	40	0	0 LED 3		
Philips	Softone ESL	ESL	12,0	E27	872790082518300	41.15	n.a.	8	96 Auto - TE	25	33	50	0	1 ESL/CFL		
Philips	Softone ESL	ESL	20,0	E27	872790082523700	41.16	n.a.	6	120 Auto - TE	25	38	60	0	10 ESL/CFL		
Philips	Tornado ESL	ESL	15,0	E27	872790092404600	41.17	n.a.	10	150 Auto - TE	25	38	65	0	0 LED 1		
Philips	MASTER LED Spot	LED	4,3	GU10	871869645709200	41.18	n.a.	40	172 Auto - TE	10	40	70	1	20 R/L/C Standard, LED2		
Philips	MASTER LED Luster	LED	6,0	E27	871829174188600	41.2	n.a.	16	96 Auto - TE	22	31	55	0	0 LED 5, LED 1	Good dimming experience	

Philips	LED Lampe	LED	6,0	E27	871829176246100	41.3	18	108	Auto - TE	24	36	60	0	0	LED 1	
Philips	Master LED Bulb	LED	7,0	E27	871829167196100	41.4	6	42	Auto - TE	20	45	65	0	0	LED 1	
Philips	MASTER LED BULB Dimtone	LED	8,0	E27	871829119200800	41.5	12	96	Auto - TE	25	40	60	0	0	LED 1	no smooth start - then OK
Philips	Corepro LED Bulb	LED	10,0	E27	871829174741300	41.6	12	120	Auto - TE	20	34	75	0	0	LED 2	
Philips	MASTER LED BULB	LED	18,0	E27	871829175856300	41.7	4	72	Auto - TE	14	40	70	0	0	LED 4, R/L/C Standard	
Philips	Master LED Luster	LED	3,5	E14	871829174325500	41.8	28	98	Auto - TE	8	26	45	0	0	LED 3	Good dimming experience
Philips	LED Spot	LED	4,0	E14	871829119292300	41.9	30	120	Auto - TE	17	28	40	0	0	LED 3	
Eglo	LED Globelampe 3000K matt 600lm dimmbar	LED	9,0	E27	9002759111861	42.1	4	36	Auto - TE	24	45	75	0	0	LED 1	
Eglo	Eglo LED Spot GU10 38° 6W 390 lm dimmbar	LED	6,0	GU10	9002759114534	42.2	11	66	Auto - TE	20	45	70	0	0	LED 2	
Paulmann	LED 230V	LED	11,0	E27	400087028142000	43.1	6	66	Auto - TE	25	45	70	0	0	LED 1	
Paulmann	LED 230V	LED	4,0	GU10	400087028144400	43.2	8	32	Auto - TE	24	40	70	0	0	LED 1	
Osram	LED SUPERSTAR CLASSIC P advanced	LED	3,8	E27	4008321992352	44.1	36	136,8	Auto - TE	12	28	45	0	0	LED 3	no smooth start - then OK
Osram	LED SUPERSTAR CLASSIC B	LED	4,0	E14	4008321994035	44.2	12	48	Auto - TE	12	30	70	0	0	LED 4, R/L/C Standard	
Osram	LED SUPERSTAR CLASSIC A advanced	LED	13,5	E27	4052899914384	44.3	10	135	Auto - TE	18	40	70	0	0	LED 4, R/L/C Standard	Slow reaction
Osram	LED SUPERSTAR CLASSIC A advanced	LED	6,0	E27	4052899911161	44.4	20	120	Auto - TE	26	46	70	0	0	LED 1	
Osram	LED SUPERSTAR CLASSIC B advanced	LED	6,0	E14	4052899911413	44.5	23	138	Auto - TE	18	28	45	0	0	LED 3	no smooth start - then OK
Osram	LED SUPERSTAR PAR16 advanced	LED	3,0	GU10	4008321881816	44.6	8	24	Auto - TE	20	40	70	0	0	LED 2	
Osram	LED SUPERSTAR CLASSIC P advanced	LED	6,0	E27	4052899911475	44.7	22	132	Auto - TE	16	28	40	0	0	LED 3	no smooth start - then OK
Osram	Leuchtstofflampe DIM	ESL	15,0	E27	DINT DIM GL 15W/825	44.8	8	120	Auto - TE	38	55	80	0	3	ESL/CFL	
Havells-Sylvania	ToLEdo Candle Dim Frosted 250LM E14 SL	LED	4,5	E14	5410288269252	45.1	10	45	Auto - TE	25	45	75	0	0	LED 1	
Havells-Sylvania	TOLEDO 470LM DIM	LED	6,5	E14	5410288269450	45.2	6	39	Auto - TE	25	40	70	0	0	LED 1	
Havells-Sylvania	TOLEDO+ AGL A60 DIM	LED	12,0	E27	5410288264288	45.3	13	156	Auto - TE	23	36	70	0	0	LED 1	Good dimming experience
Havells-Sylvania	REFLED+ ES50 345LM	LED	6,5	GU10	5410288267906	45.4	8	52	Auto - TE	20	45	75	0	0	LED 2	
Samsung	CL B 15000H DIM KLAR	LED	5,2	E14	8806085179721	46.1	25	130	Auto - TE	32	47	65	0	0	LED 6, LED 1	
Samsung	CL A 25000H 300° DIM	LED	13,5	E27	8806085179738	46.2	3	40,5	LE	25	40	75	0	0	LED 7	
Müller Licht	LED Leuchtmittel E27 EB1400369	LED	7,0	E27	20016647 / 25895	48.1	25	175	Auto - TE	20	40	80	0	0	LED 2	Good dimming experience
Müller Licht	LED Leuchtmittel E14 EB1400369	LED	5,5	E14	25898	48.2	8	44	Auto - TE	25	45	70	0	0	LED 1	
Müller Licht	LED Leuchtmittel EU10 EB1400378	LED	4,0	GU10	20017392 / 23822	48.3	7	28	Auto - TE	22	40	65	0	0	LED 1	
SG	Capella Soft	LED	2		7021989970361	49.1	62	124	Auto - TE	25	40	70	0	0	LED 1	
SG	Junistar Exclusive 10W Prod.Nr.: 912310 + Tridonic LCBI 15W Art.Nr.: 89800267	LED	10		7021989123101	49.10	8	80	Auto - TE	9	28	69	1	10	LED 3	
SG	Junistar Asym. Optidim 10W Prod.Nr.: 912370 + Tridonic LCBI 15W 89800267	LED	10		7021989123705	49.11	15	150	Auto - TE	10	38	70	1	10	LED 2	
SG	Junistar Soft 10W - Prod.Nr.: 912076 + Tridonic LCBI 15W Art.Nr.: 87500386	LED	10		7021989120766	49.12	19	190	Auto - TE	10	36	60	1	10	LED 4, LED 1	
SG	Uniled 10W - Prod.Nr.: 997276 + Philips Xitanium 10W Art.Nr.: 9290009322	LED	10		7021989972761	49.13	5	50	Auto - TE	25	55	75	0	0	LED 1	
SG	Junistar Exclusive 10W Prod.Nr.: 912310 + Tridonic LCBI 15W Adv Art.Nr.: 87500386	LED	10		7021989123101	49.14	17	170	Auto - TE	15	36	60	1	10	LED 4, LED 1	
SG	UNILED Iosafe Prof.Nr.: 912290 + Tridonic LCA 10W Art. Nr.: 87500406	LED	8		7021989122906	49.15	25	200	Auto - TE	15	43	70	1	10	LED 2	
SG	Circulus 17W Prod.Nr.: 212000 + Osram OTe 25	LED	17		7021982120008	49.16	12	204	Auto - TE	15	44	75	0	0	LED2, R/L/C Standard	
SG	Chef LED 4x2,4W - Prod.Nr.: 391024 + Philips Xitanium 9W Art.Nr.: 9290008387	LED	9,6		7021983910240	49.17	5	48	Auto - TE	12	46	70	0	0	R/L/C Standard	
SG	Gyro DimToWarm 6W - Prod.Nr.: 912309 + Tridonic LCBI 10W Art.Nr.: 87500273	LED	6		7021989123095	49.18	20	120	Auto - TE	12	40	70	1	15	LED 2, R/L/C Standard	Great dimming experience
SG	LEDSTAR Driver Box - Prod.Nr.: 820041 with LEDSTAR 2,4W	LED	10		7021988200414	49.2	12	120	Auto - TE	20	40	80	0	0	LED 2	
SG	Jupiter LED Click-It	LED	6,5	GU10	7021989229025	49.3	20	130	Auto - TE	20	35	75	0	0	LED 2	
SG	Chef LED 2x2,4W Prod.Nr.: 391022	LED	4,8		7021983910226	49.4	13	62,4	Auto - TE	12	47	70	0	0	R/L/C Standard	
SG	Zip Star LED - Prod.Nr.: 3031	LED	5		7021980030316	49.5	20	100	Auto - TE	25	48	75	0	0	LED 1	
SG	SPA KROM LED - Prod.Nr.: 198401	LED	10		7021981984014	49.6	12	120	Auto - TE	25	50	80	0	0	LED 1	
SG	Jupiter Pro - Prod.Nr.: 940300 + Osram OTe 25	LED	25		7021989403005	49.7	8	200	Auto - TE	17	48	80	0	0	R/L/C Standard	
SG	UNILED 5W - Prod.Nr.: 912090 + Philips Xitanium 10W Art.Nr.: 9290004662	LED	5		7021989120902	49.8	25	125	Auto - TE	18	40	85	0	0	LED 2	
SG	Junistar Gyro 8W Prod.Nr.: 912300 + Tridonic LCA 10W Art. Nr.: 87500406	LED	8		7021989123002	49.9	25	200	Auto - TE	15	42	70	1	10	LED 2	
Unilamp Luzense	LED PrismaCob+	LED	6,5	GU10	7072125105369	50.1	10	130	Auto - TE	15	40	80	0	0	R/L/C Standard	
Unilamp Luzense	Gyro Warmdim & Kaoyi KEA-9E30ICD - EL.Nr.: 3229420	LED	9		7072125109671	50.10	27	243	Auto - TE	30	54	90	0	0	R/L/C Standard	Good dimming experience
Unilamp Luzense	LED Compact 1 Downlight (Kaoyi KD7R-W12EQAD/8K3I5) - EL.Nr.:329480	LED	12		7072125109374	50.11	22	264	Auto - TE	15	44	80	0	0	R/L/C Standard (1%),	
Unilamp Luzense	Limbo Integral (Kaoyi K3DR-R10EHCD/AK3P) - EL.Nr.: 3229330	LED	10		7072125107042	50.12	27	270	Auto - TE	15	43	75	0	0	R/L/C Standard (1%),	
Unilamp Luzense	PrismaCob + Warmdim - EL.Nr.: 3805742	LED	6	GU10	7072125110202	50.13	35	210	Auto - TE	15	45	90	0	0	R/L/C Standard (1%),	Good dimming experience
Unilamp Luzense	Prisma+ Warmdim - EL.Nr.: 3805730	LED	6	GU10	7072125105383	50.15	35	210	Auto - TE	15	45	90	0	0	R/L/C Standard (1%),	Good dimming experience
Unilamp Luzense	PrismaCob + Warmdim - EL.Nr.: 3805740	LED	6	GU10	7072125106953	50.16	35	210	Auto - TE	15	48	90	0	0	R/L/C Standard (1%),	
Unilamp Luzense	Gyro Frame Warmdim 2x9W & Kaoyi KAA-18E30ICD-E - EL.Nr.: 3229311	LED	18		7072125109244	50.17	15	270	Auto - TE	20	47	90	0	0	R/L/C Standard, LED 2	Good dimming experience
Unilamp Luzense	Gyro Frame 2x9W & Kaoyi KAA-18E45IAD-E - EL.Nr.: 3229436	LED	18		7072125110370	50.18	15	270	Auto - TE	18	43	90	0	0	R/L/C Standard, LED 2	
Unilamp Luzense	Gyro Frame Warmdim 3x9W (Kaoyi KAA-27E30ICD-E) - EL.Nr.: 3229312	LED	27		7072125109251	50.19	10	270	Auto - TE	20	46	90	0	0	R/L/C Standard, LED 2	Good dimming experience
Unilamp Luzense	Juno Cob+ (Kaoyi KAA-10E23IAD-2 + K3DR A 10W	LED	10		7072125105314	50.2	17	170	Auto - TE	18	35	70	1	20	LED 2	
Unilamp Luzense	Gyro Frame & Kaoyi KAA-27E45IAD-E - EL.Nr.: 3229437	LED	27		7072125110387	50.20	10	270	Auto - TE	18	41	90	0	0	R/L/C Standard, LED 2	
Unilamp Luzense	KON LED 2x3W Kaoyi KAW-6E30IAD - EL.Nr.: 3105864	LED	6		7072125109459	50.21	41	246	Auto - TE	15	42	80	0	0	R/L/C Standard (1%),	
Unilamp Luzense	MIR 60cm - EL.Nr.: 3306752	LED	10		7072125103174	50.22	25	250	Auto - TE	23	44	70	0	0	LED 1	
Unilamp Luzense	MIR 1m - EL.Nr.: 3306751	LED	14		7072125103167	50.23	13	182	Auto - TE	23	44	70	0	0	LED 1	
Unilamp Luzense	Unilamp K3DR-A10EHCD Warmdim + Kaoyi KAA-10E35I/CD	LED	10			50.3	17	170	Auto - TE	25	50	85	0	0	R/L/C Standard	
Unilamp Luzense	Juno Soft+ & Kaoyi KAA-10E35I/CD - EL.Nr.: 3229340 Warmdim	LED	10		7072125107097	50.4	27	270	Auto - TE	25	47	75	0	0	LED 1	Great dimming experience
Unilamp Luzense	Gyro & Kaoyi KEA-9E45I/CD - EL.Nr.:3229430	LED	8		7072125109701	50.5	27	216	Auto - TE	30	54	90	0	0	R/L/C Standard	Good dimming experience
Unilamp Luzense	Isocob + Kaoyi K3DR-F9EFAD/AK2R - EL.Nr.: 3229390	LED	9		7072125106939	50.6	31	279	Auto - TE	26	46	75	0	0	LED 1	
Unilamp Luzense	Juno Soft+ & Kaoyi KAA-10E23ICD - EL.Nr.: 3225310	LED	10		7072125104997	50.7	27	270	Auto - TE	25	45	80	0	0	LED 1	
Unilamp Luzense	Limbo Soft Warmdim & Kaoyi KAA-10E35I/CD - EL.Nr.: 3229325	LED	10		7072125107011	50.8	25	250	Auto - TE	24	48	80	0	0	LED 1	Good dimming experience
Unilamp Luzense	Juno Soft PRO + Kaoyi KD4R-G18EFAD/9K3N - EL.Nr.: 3229347	LED	18		7072125109343	50.9	14	252	Auto - TE	15	42	75	0	0	R/L/C Standard (1%),	
Nextec	Premium 738	LED	6,8	GU10	5908293907738	51.1	20	136	Auto - TE	23	33	45	0	0	LED5, LED3	
ISS		LED	8			52.1	20	160	Auto - TE	20	50	85	0	0	R/L/C Standard	
Quick Install	DL Allround Gyro - EL.Nr.: 3234445	LED	10		7070938053754	53.1	8	80	Auto - TE	30	58	80	0	0	R/L/C Standard	
Quick Install	DL Eco - EL.Nr.: 3234450	LED	6		7070938053631	53.2	35	210	Auto - TE	12	44	65	0	0	R/L/C Standard (1%), LED 4	Great dimming experience
Quick Install	QI 6W/GU10 - EL.Nr.: 3787000	LED	6	GU10	7070938053617	53.3	8	48	Auto - TE	16	48	70	25	1	LED 2	
Collingwood	H2 Pro 550 T - Cat.Nr.: DLT35660WW	LED	8,5		5055351501923	54.1	6	51	Auto - TE	10	50	75	20	1	R/L/C Standard (1%),	
Betek	Nova LED DL + Eagle Rise ELP009C0350LSD - EL.Nr.: 3253602	LED	8			55.1	6	48	Auto - TE	28	58	80	0	0	LED 1	
Betek	Lido LED DL + Eagle Rise ELP009C0350LSD - EL.Nr.: 3253600	LED	6			55.2	6	36	Auto - TE	30	58	80	0	0	LED 1	
Qlight	Leo Tilt DL + AcTEC D18009NT-N3 - EL.Nr.: 3234370	LED	7		7090037700014	56.1	26	175	Auto - TE	18	42	70	0	0	LED 2	

Status: 10.11.2015

Profile Name	Category ID	Profile ID	Dim-Type	MIN	MID	MAX	Warmup / s	0%	10%	20%	30%	40%	50%	60%	70%	80%	90%	100%
R/L/C Standard (15 - 48 - 80 Auto)	0	1	Auto	15	48	80	0	15	22	28	35	41	48	54	61	67	74	80
LED 1 (26 - 43 - 68 Auto)	0	2	Auto	26	43	68	0	26	29	32	35	39	43	47	52	57	62	68
LED 2 (20 - 40 - 75 Auto)	0	3	Auto	20	40	75	0	20	23	26	30	35	40	46	52	59	67	75
LED 3 (15 - 30 - 45 Auto)	0	4	Auto	15	30	45	0	15	18	21	24	27	30	33	36	39	42	45
CFL/ESL (35 - 50 - 70 Auto 3s)	0	5	Auto	35	50	70	3	35	38	40	44	47	50	54	58	62	66	70
ON/OFF only	0	6	Switch	100	100	100	0	100	100	100	100	100	100	100	100	100	100	100
LED 4 (15 - 35 - 70 Auto)	0	7	Auto	15	35	70	0	15	18	21	25	30	35	41	47	54	62	70
LED 5 (20 - 30 - 50 Auto)	0	8	Auto	20	30	50	0	20	21	23	25	27	30	33	37	41	45	50
LED 6 (30 - 37 - 50 Auto)	0	9	Auto	30	37	50	0	30	31	32	33	35	37	39	42	44	47	50
LED 7 (25 - 40 - 70 Leading Edge)	0	10	Leading Edge	25	40	70	0	25	27	29	32	36	40	45	50	56	63	70